

2638

STYLE BASIC HANDSET FOR A/V SYSTEMS





Telephone with electronic call call tone adjustment, privacy of speech, call tone privacy, door open pushbutton and supplementary pushbutton for porter switchboard call or free (C/N.O.). By means of selection jumper, the second pushbutton can be used to control actuator art. 1256. Allows management of the local floor call and call repetition. Complete with dip-switch with 8 positions for selection of the desired user code. With this model, addition of pushbuttons or supplementary LEDs is not possible. Dimensions: 95X215X58 mm. From the RI006 it is compatible with all Simplebus 2 functions and products.





2638

STYLE BASIC HANDSET FOR A/V SYSTEMS

	GENERAL DATA
Height (mm)	215
Width (mm)	95
Depth (mm)	58
Type of finishing materials	Plastic
Product weight (g)	0.42
Wall-mounted	Yes
Desk base-mounted	Yes

ELECTRICAL CHARACTERISTICS

Supply voltage

22÷28VDC

HARDWARE FEATURES	
Clamps	L L CFP CFP C3 P3 S- S+
Total buttons (n°)	2

ENVIRONMENTAL AND COMPLIANCE FEATURES	
IP protection rating	IP30
Operating temperature (°C)	-5 ÷ 40

GENERAL FEATURES	
Maximum current absorption (mA)	200
Minimum current absorption (mA)	1
Switchboard call function	Yes
Floor door call function	Yes
Actuator control function	Yes
Privacy conversation function	Yes
Privacy function	Yes
Key button function	Yes
Loudspeaker volume control	Yes
Microphone volume control	Yes

The technical specifications are subject to change without prior notice.





STYLE BASIC HANDSET FOR A/V SYSTEMS

GENERAL FEATURES	
Ringtone volume control	Yes
Redial	Yes
Audio system	Yes
Simplebus 2 audio system	Yes
Simplebus 2 audio/video system	Yes
Electronic bell	Yes





STYLE BASIC HANDSET FOR A/V SYSTEMS

ACCESSORIES

	2642W/28	White desk conversion kit for all the telephones in the Style series. Complete with 1.5 mt of white cable and connection bushing fitted with 28 connection terminals. Dimensions 84X189X32 mm.
-	2642W/16	WHITE DESK BASE FOR STYLE 16 WIRE White desk conversion kit for all the telephones in the Style series. Complete with 1.5 mt of white cable and connection bushing fitted with 16 connection terminals. Dimensions 84X189X32 mm.
	2600/5	RED COVER ACCESSORY FOR STYLE ELEGANCE DOOR ENTRY PHONE Red facia for Style elegance version telephone
	2600/4	ORANGE FACIA FOR STYLE ELEGANCE Orange facia for Style elegance version telephone
	2600/3	BLACK COVER FOR STYLE ELEGANCE Black facia for Style elegance version telephone
	2600/2	GREEN FACIA FOR STYLE ELEGANCE Green facia for Style elegance version telephone
	2600/1	PALE BLUE FACIA FOR STYLE ELEGANCE Pale blue facia for Style elegance version telephone





STYLE BASIC HANDSET FOR A/V SYSTEMS

ACCESSORIES

ţ.	1627B	ACCESSORY - 1 ADDITIONAL LED FOR STYLE INTERCOM - BLACK Blue LED to be inserted in the base of the telephone. Takes up the space of one element. 12-24V AC-DC operation.
ţ.	1627	LED FOR STYLE ELEGANCE H/SET Blue LED to be inserted in the base of the telephone. Takes up the space of one element. 12-24V AC-DC operation.
	1626	STYLE INTERCOM ADDITIONAL PUSH BUTTON Pushbutton to be inserted in the base of the telephone. Takes up the space of one element.
	1214/2C	VIDEO FILTER FOR S2 SYSTEM Line branch terminal for colour monitors. The terminal must be connected on the riser to be branched towards brackets or telephones.

